

GD500F

Quick Reference Guide

Basic Setting operation:

- Step 1:** Operate with the main machine's standard mode "Normal Open"
- Step 2:** Switch to the correct speed(pulse) of coin machine: FAST 25ms, MEDIUM 45ms and SLOW 65ms
- Step 3:** Connect the +12V DC and Ground wiring for the coin Acceptor.
- Step 4:** Set the switch from "Start" to "Set" position, the LED light will show "00", press the switch which for adjusting the coin's value, to adjust the coin value when the coin programming. "00-99" means how many times of the out pulse signal will be sent when the programmed coin was deposited, return the switch from "Set" to "Start", setting finished.
- Step 5:** Set the switch from "NOM" to "MGN" position, then turn the switch from "Start" to "Set" position, the LED show default "P1", "P1-P9" means a output signal needs how many programmed coins to be deposited like "P1, P2, P3...P9"
- Step 6:** Prepare the needed sample coins.
- Step 7:** Insert 10pcs coins in turn to set the coin (time interval 0.3 seconds)
- Step 8:** Turn the coin set switch to "Start" and finished the setting.